

TABTIME SUPER 8 INSTRUCTIONS

TABTIME SUPER 8 can alarm up to 8 times per day at the exact times you choose and remembers your alarm settings every day.

TTS8 also has 8 tablet compartments numbered to correspond with each alarm.

There is also a Countdown function for regular doses. i.e every $\frac{1}{2}$ - $1\frac{1}{2}$ - $2\frac{1}{4}$ - $3\frac{3}{4}$ hours etc

TTS8 has a back up safety feature to ensure you remember to take your medication. The flashing red LED on the lid of TTS8 begins to flash at the same time as the audio alarm & will continue to flash until you open the box to take your tablet. So if the LED is flashing it indicates that you have not taken your last dose of medication. Please note that extended use of this feature will reduce the life of the battery.

TTS8 has a HI/LO volume switch. Choose whichever volume suits you the best

TABTIME SUPER 8 has 10 functions controlled by 3 control buttons.

Pressing the MODE button 1 allows you to set the TIME

Press Mode 2-3-4-5-6-7-8-9 to set up to 8 ALARMS

Press 10 to set the COUNTDOWN function for regular alarm settings.

Note- the Countdown function cannot be used in conjunction with the variable time alarms

If you make a mistake during programming, you must return to function 1 and start over again.

TABTIME SUPER 8 has a 24 hour clock and all settings start in the a.m.

TO SET THE TIME. (FUNCTION 1)

REMOVE THE PLASTIC INSULATING STRIP TO CONNECT THE BATTERY

Press and hold the MODE button until the display flashes. Set the TIME using the HOUR & MINUTE buttons. Confirm the TIME by pressing the MODE button. The TIME is now displayed

TO SET UP TO 8 ALARMS (FUNCTIONS 2-9)

Press the MODE button and a --:-- display and number 1 with a bell appears at the top of the screen. Press and hold the MODE button until the --:-- display flashes then set the time you require the first alarm using the HOUR & MINUTE buttons. Press MODE to confirm alarm 1 is set.

Press MODE button to set alarms 2-3-4-5 etc by repeating this process.

At alarm time, the audio alarm will beep for 40 seconds and the red LED will begin to flash. Both alarms are cancelled by opening the box. (You can also press the MINUTE button to stop the alarm beeping)

The flashing LED on the lid of Super 8 will continue to flash until you open the box to take your tablet. So if you take TTS8 out of your pocket or purse and the LED is flashing, you have forgotten to take your last dose!

TO SET THE COUNTDOWN TIMER (FUNCTION 10)

Press the MODE button 10. You will now see an egg timer symbol on the top left of the screen and the display shows 00:00. Press MODE until the symbol 0.00 flashes then set the time you require for the interval between doses i.e $1\frac{1}{4}$ - $2\frac{1}{2}$ - $3\frac{3}{4}$ hours etc. Press the MINUTE button to start the Countdown and the egg timer symbol will begin to flash to confirm the Countdown timer is operating. Press the MODE button to return to Real Time and the beeper will alarm at the interval you chose. After the first alarm Press the MINUTE button again to start the next Countdown sequence.

CANCELLING AN ALARM

To delete any alarm; Go to the alarm 1-8 you wish to delete by pressing the MODE button and press the MINUTE button to delete that alarm. To change all settings take the battery out for a few minutes

TROUBLESHOOTING.

Check the battery power indicator is at least 2 bars. If your Tabtime starts to act strangely, the figures fade or the Alarm rings randomly etc it is time to change the battery which can be bought at most supermarkets or jewellers. If you find the catches on the tablet compartments stiff file a little off each catch with a nail file

DISCLAIMER. This product must be regarded as purely an aid to memory and Tabtime Ltd or their agents cannot be held responsible if you forget to take your medication, take the wrong medication, take the wrong medication at the wrong time or any combination of these events.